


AMD-103 BR

COMPACT WIRELESS MAGNETIC DETECTOR FOR ABAX SYSTEMS

Compact magnetic door and window opening detector is designed for ABAX wireless installations. Small footprint allows to use it in these places where the aesthetics of installation components and their minimal impact to the interior design is of the highest priority.

- CR2477N supply battery
- built-in tamper detection

Supported by the controller **ACU-100 / ACU-250** (software version 4.02 or newer) and by the control panel **INTEGRA 128-WRL** (electronics version 2.1 or newer; software version 1.11 or newer).



TECHNICAL DATA

Battery working time (in years)	Estimated 2 years ^a
Operating temperature range	-10...+55 °C
Max. current consumption	14 mA
Weight	40 g
Maximum humidity	93 ±3%
Operating frequency band	868,0 ÷ 868,6 MHz
Radio communication range (in open area)	up to 350 m
Battery	CR2477N 3V
Standby current consumption	10 µA
Environmental class according to EN50130-5	II
Detector enclosure dimensions	32 x 45 x 20 mm
Dimensions magnet enclosure	11 x 45 x 10 mm